

# Connectors

## Connectors for up to 12/24A size.

TYPE	DESCRIPTION	MODEL	MAX CROSS SECTION
C1	24V-DC/STO A-B	MINI COMBICON, MC 1.5/4-G-3,81	1,5mm <sup>2</sup>
C2	RS232	D-SUB 9 pins male	0,5mm <sup>2</sup>
C3	Motor	COMBICON POWER, HC/6-G-7.62	2,5mm <sup>2</sup>
C4	AC Connection	COMBICON POWER, HC/9-G-7.62	2,5mm <sup>2</sup>
C5	Input/output signals	MINI COMBICON, MC 1.5/12-G-3,81	1,5mm <sup>2</sup>
C6	Motor Feedback	D-SUB 15 pins femmina	0,5mm <sup>2</sup>
C7	Can (opt. Analog Input)	D-SUB 9 pins femmina	0,5mm <sup>2</sup>
C8	Can	D-SUB 9 pins femmina	0,5mm <sup>2</sup>
C9	Back-Up/Analog Input	MINI COMBICON, MC 1.5/4-G-3,81	1,5mm <sup>2</sup>

## Connectors for 30/60A and 42/84A sizes

TYPE	DESCRIZIONE	MODEL	MAX CROSS SECTION
C1	24V-DC/STO A-B	COMBICON, MSTB-2,5/4-GF-5,08	1,5mm <sup>2</sup>
C2	RS232	D-SUB 9 pins male	0,5mm <sup>2</sup>
C3	Motor	HDFK 10	10mm <sup>2</sup>
C4	AC Connection	HDFK 10	10mm <sup>2</sup>
C5	Input/output signals	MINI COMBICON, MC 1.5/12-G-3,81	1,5mm <sup>2</sup>
C6	MotorFeedback	D-SUB 15 pins female	0,5mm <sup>2</sup>
C7	Can (opt. Analog Input)	D-SUB 9 pins female	0,5mm <sup>2</sup>
C8	Can	D-SUB 9 pins female	0,5mm <sup>2</sup>
C9	Back-Up/Analog Input	MINI COMBICON, MC 1.5/4-G-3,81	1,5mm <sup>2</sup>
C10	Electromechanical Brake	COMBICON, MSTB-2,5/2-GF-5,08	2,5mm <sup>2</sup>

From:

<https://dokuwiki.nilab.at/> - **NiLAB GmbH**  
**Knowledgebase**

Permanent link:

[https://dokuwiki.nilab.at/doku.php?id=mbd\\_servo\\_drive:connectors](https://dokuwiki.nilab.at/doku.php?id=mbd_servo_drive:connectors)

Last update: **2023/09/21 07:16**

